

INSTALLATION PARAMETERS FOR CONNER DRIVES (ALL MODELS)

sold by: MIDEX COMPUTER SPARES

PLEASE NOTE: NO LOW LEVEL FORMATTING !!!!!

| <u>Model</u> | <u>I/Face</u> | <u>Hds</u> | <u>Cyl</u> | <u>S/Trk</u> | <u>Type</u> | <u>Table</u> | <u>F/cap</u> |
|--------------|---------------|------------|------------|--------------|-------------|--------------|--------------|
| CP3000 | AT/IDE | 5 | 977 | 17 | 17 | 1 | 42MB |
| CP30064 | AT/IDE | 4 | 762 | 39 | USER | 2 | 64MB |
| CP2064 | AT/IDE | 4 | 823 | 38 | USER | 3 | 64MB |
| CP2084 | AT/IDE | 8 | 548 | 38 | USER | 3 | 84MB |
| CP30084E | AT/IDE | 4 | 903 | 46 | USER | 4 | 84MB |
| CP2088 | AT/IDE | 8 | 548 | 38 | USER | 3 | 84MB |
| CP30100* | SCSI-2 | 4 | 1522 | 39 | 0 | SCSI | 120MB |
| CP30104 | AT/IDE | 8 | 762 | 39 | USER | 2 | 120MB |
| CP30174E | AT/IDE | 8 | 903 | 46 | USER | 4 | 170MB |
| CP3200F* | SCSI-2 | 8 | 1366 | 38 | 0 | SCSI | 212MB |
| CP3204F | AT/IDE | 16 | 683 | 38 | USER | 3 | 212MB |
| CP3360* | SCSI-2 | 8 | 1806 | 49 | 0 | SCSI | 362MB |
| CP3364 | AT/IDE | 16 | 702 | 63 | USER | 4 | 362MB |
| CP3540* | SCSI-2 | 16 | 987 | 38 | 0 | SCSI | 543MB |
| CP3544 | AT/IDE | 16 | 1024 | 63 | USER | 4 | 510MB |

* ALL SCSI MODEL SPECS. SUPPLIED ARE TRUE PHYSICAL PARAMETERS, HOWEVER CMOS DRIVE TYPE ZERO (NONE) MUST BE SELECTED).

- ALL AT/BUS MODEL SPECS. ARE BASED ON UNIVERSAL TRANSLATION MODE (UTM) CONVERSIONS.

AT/IDE MASTER/SLAVE JUMPERS

1. SINGLE DRIVE = JUMPER ACT & CD
MASTER DRIVE = JUMPER ACT, CD & DSP
SLAVE DRIVE = NO JUMPERS
2. SINGLE DRIVE = JUMPER E2 N/A
MASTER DRIVE = JUMPER E1 & E2
SLAVE DRIVE = NO JUMPERS
3. SINGLE DRIVE = JUMPER CD
MASTER DRIVE = JUMPER CD & DSP
SLAVE DRIVE = NO JUMPERS
4. SINGLE/MASTER DRIVE = JUMPER CD
SLAVE DRIVE = NO JUMPERS

SCSI ID JUMPERS

| SCSI ID | E1 | E2 | E3 |
|---------|-----|-----|-----|
| ID 0 | OUT | OUT | OUT |
| ID 1 | IN | OUT | OUT |
| ID 2 | OUT | IN | OUT |
| ID 3 | IN | IN | OUT |
| ID 4 | OUT | OUT | IN |
| ID 5 | IN | OUT | IN |
| ID 6 | OUT | IN | IN |
| ID 7 | IN | IN | IN |

DO NOT follow DOS-5 installation prompt - simply FDISK & FORMAT C:/S as with DOS-3.3. DO NOT follow DOS-5 prompt ie: answer 'NO' to install and perform FDISK & FORMAT C:/S manually.



MIDX

MIDEX COMPUTER SPARES

TEL: 802-5010

PAUL TWOCO

| | | | | | | |
|--------------|------------------------------|--------------------------------|-------------------------------|--------------|-------|------|
| ST506 /MFM | ST251-1 | 5¼"HH | 40MB | 28MS | 799 | |
| | ST4097 | 5¼"FH | 80MB | 28MS | 1750 | |
| | XT2190R | 5¼"FH | 160MB | 28MS (REFBD) | 3600 | |
| | ST21M | MFM HARD ONLY CONTROLLER | | | 100 | |
| ATBUS /IDE | ST9051A | 2½" | 42MB | 18MS | 682 | |
| | ST351A | 3½"1"H | 42MB | 28MS | 528 | |
| | CP3000 | 3½"1"H | 42MB | 28MS | 550 | |
| | CP30084 | 3½"1"H | 84MB | 17MS | 750 | |
| | ST3120A | 3½"1"H | 105MB | 18MS | 890 | |
| | CP30104 | 3½"1"H | 120MB | 18MS | 975 | |
| | ST3144A | 3½"1"H | 130MB | 18MS | 965 | |
| | CP30174 | 3½"1"H | 170MB | 18MS | 1100 | |
| | CP3204 | 3½"HH | 212MB | 15MS | 1580 | |
| | ST3283A | 3½"1"H | 245MB | 12MS | 1859 | |
| | CP3364 | 3½"HH | 362MB | 12MS | 2950 | |
| | ST1400A | 3½"HH | 331MB | 14MS | 2360 | |
| | ST1480A | 3½"HH | 426MB | 14MS | 2950 | |
| | CP3544 | 3½"HH | 510MB | 12MS | 3800 | |
| | ATBUS | HARD & FLOPPY CONTROLLER | | | 50 | |
| | ULT15C | ATBUS/IDE CACHE IMB CONTROLLER | | | 850 | |
| | ESDI | ST4383E | 5¼"FH | 338MB | 18MS | 4090 |
| | | ULT12F | ESDI HARD & FLOPPY CONTROLLER | | | 580 |
| | SCSI | CP30100 | 3½"1"H | 120MB | 15MS | 1100 |
| ST1239N | | 3½"HH | 204MB | 15MS | 2060 | |
| CP3200 | | 3½"HH | 212MB | 15MS | 1650 | |
| ST3283N | | 3½"1"H | 248MB | 12MS | 1991 | |
| ST4385N | | 5¼"FH | 337MB | 10.7MS | 4365 | |
| CP3360 | | 3½"HH | 362MB | 12MS | 2950 | |
| ST1480N | | 3½"HH | 426MB | 14MS | 3910 | |
| CP3540 | | 3½"HH | 543MB | 12MS | 3800 | |
| ST4766N | | 5¼"FH | 676MB | 15MS | 4260 | |
| ST41200N | | 5¼"FH | 1050MB | 16MS | 5700 | |
| ST41650N | | 5¼"FH | 1420MB | 15MS | 6650 | |
| ST42100N | | 5¼"FH | 1900MB | 12.9MS | 8300 | |
| ST42400N | | 5¼"FH | 2100MB | 11MS | 10400 | |
| ULT14F | | SCSI HARD & FLOPPY + DRIVERS | | | 730 | |
| AHA1542B | | SCSI HDD & FLPY HOST ADAPTOR | | | 730 | |
| AHA1542B-KIT | SCSI HARD & FLOPPY + DRIVERS | | | 880 | | |

PRICES AND SPECIFICATIONS SUBJECT TO CHANGE WITHOUT NOTICE.
RETAIN PACKAGING FOR WARRANTY SWOPS.

PRICES EXCLUDE VAT

05 OCTOBER 92